



The image shows a red Uni-T UT171C digital multimeter. The LCD display shows the date 15/10/22, time 11:11, and a frequency reading of 0.000 kHz. The main display shows 0.0000 with a voltage symbol (V) and a range of 6V. Below the display, it says 'Industrial OLED Digital Multimeter' and '68000 Counts'. The device has various buttons for functions like RANGE, STONE, RECALL, and SETUP, as well as a large rotary selector switch. The bottom of the device shows input ports for 10A, mA, A, COM, and VΩkΩ.

- UNI-T
- Digital multimeter CAT III 1000V/ CAT IV 600V
- OLED backlight display up to 60000 counts
- DC and AC voltage measurement up to 1000 V
- DC and AC current measurement up to 10 A
- Analogue bar display
- Bandwidth up to 100kHz
- LPF filter
- High accuracy in AC with built-in True RMS function
- High impedance for DCV 1 GOhm
- Resistance, Capacitance and Frequency Measurement
- Temperature measurement between -40°C~1000°C
- Relative mode
- NVC/Data hold/MAX/MIN functions
- Memory of up to 9999 data USB and Bluetooth connection
- Buzzer for continuity test
- Diode test

- Automatic shutdown